



DATA SHEET

# VHF UHF DAS Antenna

MULTI-POLARIZED OUTDOOR DAS ANTENNA

MODEL NO:

**08-ANT-0908ST**

## Features

- Multi-Polarized
- Maximum Signal Stability
- Built In Spatial Diversity
- RoHS Compliant
- Compact Design

## Applications

- Outdoor DAS, BDA Systems
- Remote Monitoring
- Stadiums
- Parking Garages
- High Obstruction Deployments



## Product Overview

The Omni DAS Antenna is the latest in Multi-Polarized technology providing superior patterning and continuous performance for fixed voice communications. Available in numerous frequency ranges with a 12MHz Bandwidth (\*\*See Chart for Part Numbers and Frequencies\*\*) The Omni DAS Antenna allows users to transmit and receive in real world environments where other antennas fail to connect. Installs easily with 3/4 inch stud mount.

## Electrical Data

- Frequency Range: Various, See Chart Below.
- Gain: Unity\*
- VSWR: < 2:1
- Horizontal Pattern Type: Full
- Vertical Pattern Type: Omnidirectional
- Ground Plane: Built-In
- Min Ground Plane Size: N/A

## General Data

- Color: White or Black
- Antenna Feeds: One
- Connector: N-Male
- Coax Length: 1 ft
- Coax Type: Low Loss 200 Series
- Polarization: Multi-Polarized
- Power: 50 Watts Input
- Input: 50 ohms nominal

\* With built in spatial and polarization diversity, performance in obstructed environments is greater than that of standard antennas with similar or higher laboratory gains.

## Environmental Data

- Construction: UV Stabilized ASA
- Environmental Conditions: Outdoor
- Operation Temperature: -40 to 85 deg C
- Storage Temperature: -40 to 85 deg C
- Transport Temperature: -40 to 85 deg C
- IP Rating: IP67

## Mechanical Data

- Diameter: 4.75 in
- Height: 5.75 in
- Weight: 7 oz
- Mounting Type: 3/4in Stud Mount
- Hardware Included: Nut/Washer

MP Antenna, LTD.  
147 Eady Court  
Elyria, Ohio 44035  
440 387 5968 *phone*  
877 678 3245 *fax*  
sales@mpantenna.com  
www.mpantenna.com

rethink the antenna™

MP Antenna reserves the right to change product information and specifications without notice. Responsibility for the use and application of MP Antenna products rests with the end user since MP Antenna cannot be aware of all potential uses. MP Antenna makes no warranties as to the fitness, merchantability, or suitability of any MP Antenna products for any specific or general uses. MP Antenna shall not be liable for incidental or consequential damages of any kind.\* MP Antenna products and technology are protected under one or more of the United States Patents 6,496,152 6,806,841 7,030,831 7,138,956 7,236,129 7,348,933 7,791,555 7,916,097 D,623,633 D,634,308 and other United States and Foreign patents applied for.



# OMNI DAS Antenna

## MULTI-POLARIZED DAS ANTENNA

### Product Overview

PN: 08-ANT-0908ST-150	Frequency Range: 144MHz – 156MHz	PN: 08-ANT-0908ST-192	Frequency Range: 186MHz – 198MHz
PN: 08-ANT-0908ST-151	Frequency Range: 145MHz – 157MHz	PN: 08-ANT-0908ST-193	Frequency Range: 187MHz – 199MHz
PN: 08-ANT-0908ST-152	Frequency Range: 146MHz – 158MHz	PN: 08-ANT-0908ST-194	Frequency Range: 188MHz – 200MHz
PN: 08-ANT-0908ST-153	Frequency Range: 147MHz – 159MHz	PN: 08-ANT-0908ST-195	Frequency Range: 189MHz – 201MHz
PN: 08-ANT-0908ST-154	Frequency Range: 148MHz – 160MHz	PN: 08-ANT-0908ST-196	Frequency Range: 190MHz – 202MHz
PN: 08-ANT-0908ST-155	Frequency Range: 149MHz – 161MHz	PN: 08-ANT-0908ST-197	Frequency Range: 191MHz – 203MHz
PN: 08-ANT-0908ST-156	Frequency Range: 150MHz – 162MHz	PN: 08-ANT-0908ST-198	Frequency Range: 192MHz – 204MHz
PN: 08-ANT-0908ST-157	Frequency Range: 151MHz – 163MHz	PN: 08-ANT-0908ST-199	Frequency Range: 193MHz – 205MHz
PN: 08-ANT-0908ST-158	Frequency Range: 152MHz – 164MHz	PN: 08-ANT-0908ST-200	Frequency Range: 194MHz – 206MHz
PN: 08-ANT-0908ST-159	Frequency Range: 153MHz – 165MHz	PN: 08-ANT-0908ST-201	Frequency Range: 195MHz – 207MHz
PN: 08-ANT-0908ST-160	Frequency Range: 154MHz – 166MHz	PN: 08-ANT-0908ST-202	Frequency Range: 196MHz – 208MHz
PN: 08-ANT-0908ST-161	Frequency Range: 155MHz – 167MHz	PN: 08-ANT-0908ST-203	Frequency Range: 197MHz – 209MHz
PN: 08-ANT-0908ST-162	Frequency Range: 156MHz – 168MHz	PN: 08-ANT-0908ST-204	Frequency Range: 198MHz – 210MHz
PN: 08-ANT-0908ST-163	Frequency Range: 157MHz – 169MHz	PN: 08-ANT-0908ST-205	Frequency Range: 199MHz – 211MHz
PN: 08-ANT-0908ST-164	Frequency Range: 158MHz – 170MHz	PN: 08-ANT-0908ST-206	Frequency Range: 200MHz – 212MHz
PN: 08-ANT-0908ST-165	Frequency Range: 159MHz – 171MHz	PN: 08-ANT-0908ST-207	Frequency Range: 201MHz – 213MHz
PN: 08-ANT-0908ST-166	Frequency Range: 160MHz – 172MHz	PN: 08-ANT-0908ST-208	Frequency Range: 202MHz – 214MHz
PN: 08-ANT-0908ST-167	Frequency Range: 161MHz – 173MHz	PN: 08-ANT-0908ST-209	Frequency Range: 203MHz – 215MHz
PN: 08-ANT-0908ST-168	Frequency Range: 162MHz – 174MHz	PN: 08-ANT-0908ST-210	Frequency Range: 204MHz – 216MHz
PN: 08-ANT-0908ST-169	Frequency Range: 163MHz – 175MHz	PN: 08-ANT-0908ST-211	Frequency Range: 205MHz – 217MHz
PN: 08-ANT-0908ST-170	Frequency Range: 164MHz – 176MHz	PN: 08-ANT-0908ST-212	Frequency Range: 206MHz – 218MHz
PN: 08-ANT-0908ST-171	Frequency Range: 165MHz – 177MHz	PN: 08-ANT-0908ST-213	Frequency Range: 207MHz – 219MHz
PN: 08-ANT-0908ST-172	Frequency Range: 166MHz – 178MHz	PN: 08-ANT-0908ST-214	Frequency Range: 208MHz – 220MHz
PN: 08-ANT-0908ST-173	Frequency Range: 167MHz – 179MHz	PN: 08-ANT-0908ST-215	Frequency Range: 209MHz – 221MHz
PN: 08-ANT-0908ST-174	Frequency Range: 168MHz – 180MHz	PN: 08-ANT-0908ST-216	Frequency Range: 210MHz – 222MHz
PN: 08-ANT-0908ST-175	Frequency Range: 169MHz – 181MHz	PN: 08-ANT-0908ST-217	Frequency Range: 211MHz – 223MHz
PN: 08-ANT-0908ST-176	Frequency Range: 170MHz – 182MHz	PN: 08-ANT-0908ST-218	Frequency Range: 212MHz – 224MHz
PN: 08-ANT-0908ST-177	Frequency Range: 171MHz – 183MHz	PN: 08-ANT-0908ST-219	Frequency Range: 213MHz – 225MHz
PN: 08-ANT-0908ST-178	Frequency Range: 172MHz – 184MHz	PN: 08-ANT-0908ST-220	Frequency Range: 214MHz – 226MHz
PN: 08-ANT-0908ST-179	Frequency Range: 173MHz – 185MHz	PN: 08-ANT-0908ST-221	Frequency Range: 215MHz – 227MHz
PN: 08-ANT-0908ST-180	Frequency Range: 174MHz – 186MHz	PN: 08-ANT-0908ST-222	Frequency Range: 216MHz – 228MHz
PN: 08-ANT-0908ST-181	Frequency Range: 175MHz – 187MHz	PN: 08-ANT-0908ST-223	Frequency Range: 217MHz – 229MHz
PN: 08-ANT-0908ST-182	Frequency Range: 176MHz – 188MHz	PN: 08-ANT-0908ST-224	Frequency Range: 218MHz – 230MHz
PN: 08-ANT-0908ST-183	Frequency Range: 177MHz – 189MHz	PN: 08-ANT-0908ST-225	Frequency Range: 219MHz – 231MHz
PN: 08-ANT-0908ST-184	Frequency Range: 178MHz – 190MHz	PN: 08-ANT-0908ST-226	Frequency Range: 220MHz – 232MHz
PN: 08-ANT-0908ST-185	Frequency Range: 179MHz – 191MHz	PN: 08-ANT-0908ST-227	Frequency Range: 221MHz – 233MHz
PN: 08-ANT-0908ST-186	Frequency Range: 180MHz – 192MHz	PN: 08-ANT-0908ST-228	Frequency Range: 222MHz – 234MHz
PN: 08-ANT-0908ST-187	Frequency Range: 181MHz – 193MHz	PN: 08-ANT-0908ST-229	Frequency Range: 223MHz – 235MHz
PN: 08-ANT-0908ST-188	Frequency Range: 182MHz – 194MHz	PN: 08-ANT-0908ST-230	Frequency Range: 224MHz – 236MHz
PN: 08-ANT-0908ST-189	Frequency Range: 183MHz – 195MHz	PN: 08-ANT-0908ST-231	Frequency Range: 225MHz – 237MHz
PN: 08-ANT-0908ST-190	Frequency Range: 184MHz – 196MHz	PN: 08-ANT-0908ST-232	Frequency Range: 226MHz – 238MHz
PN: 08-ANT-0908ST-191	Frequency Range: 185MHz – 197MHz	PN: 08-ANT-0908ST-233	Frequency Range: 227MHz – 239MHz



# OMNI DAS Antenna

## MULTI-POLARIZED DAS ANTENNA

PN: 08-ANT-0908ST-234	Frequency Range: 228MHz – 240MHz	PN: 08-ANT-0908ST-276	Frequency Range: 270MHz – 282MHz
PN: 08-ANT-0908ST-235	Frequency Range: 229MHz – 241MHz	PN: 08-ANT-0908ST-277	Frequency Range: 271MHz – 283MHz
PN: 08-ANT-0908ST-236	Frequency Range: 230MHz – 242MHz	PN: 08-ANT-0908ST-278	Frequency Range: 272MHz – 284MHz
PN: 08-ANT-0908ST-237	Frequency Range: 231MHz – 243MHz	PN: 08-ANT-0908ST-279	Frequency Range: 273MHz – 285MHz
PN: 08-ANT-0908ST-238	Frequency Range: 232MHz – 244MHz	PN: 08-ANT-0908ST-280	Frequency Range: 274MHz – 286MHz
PN: 08-ANT-0908ST-239	Frequency Range: 233MHz – 245MHz	PN: 08-ANT-0908ST-281	Frequency Range: 275MHz – 287MHz
PN: 08-ANT-0908ST-240	Frequency Range: 234MHz – 246MHz	PN: 08-ANT-0908ST-282	Frequency Range: 276MHz – 288MHz
PN: 08-ANT-0908ST-241	Frequency Range: 235MHz – 247MHz	PN: 08-ANT-0908ST-283	Frequency Range: 277MHz – 289MHz
PN: 08-ANT-0908ST-242	Frequency Range: 236MHz – 248MHz	PN: 08-ANT-0908ST-284	Frequency Range: 278MHz – 290MHz
PN: 08-ANT-0908ST-243	Frequency Range: 237MHz – 249MHz	PN: 08-ANT-0908ST-285	Frequency Range: 279MHz – 291MHz
PN: 08-ANT-0908ST-244	Frequency Range: 238MHz – 250MHz	PN: 08-ANT-0908ST-286	Frequency Range: 280MHz – 292MHz
PN: 08-ANT-0908ST-245	Frequency Range: 239MHz – 251MHz	PN: 08-ANT-0908ST-287	Frequency Range: 281MHz – 293MHz
PN: 08-ANT-0908ST-246	Frequency Range: 240MHz – 252MHz	PN: 08-ANT-0908ST-288	Frequency Range: 282MHz – 294MHz
PN: 08-ANT-0908ST-247	Frequency Range: 241MHz – 253MHz	PN: 08-ANT-0908ST-289	Frequency Range: 283MHz – 295MHz
PN: 08-ANT-0908ST-248	Frequency Range: 242MHz – 254MHz	PN: 08-ANT-0908ST-290	Frequency Range: 284MHz – 296MHz
PN: 08-ANT-0908ST-249	Frequency Range: 243MHz – 255MHz	PN: 08-ANT-0908ST-291	Frequency Range: 285MHz – 297MHz
PN: 08-ANT-0908ST-250	Frequency Range: 244MHz – 256MHz	PN: 08-ANT-0908ST-292	Frequency Range: 286MHz – 298MHz
PN: 08-ANT-0908ST-251	Frequency Range: 245MHz – 257MHz	PN: 08-ANT-0908ST-293	Frequency Range: 287MHz – 299MHz
PN: 08-ANT-0908ST-252	Frequency Range: 246MHz – 258MHz	PN: 08-ANT-0908ST-294	Frequency Range: 288MHz – 300MHz
PN: 08-ANT-0908ST-253	Frequency Range: 247MHz – 259MHz	PN: 08-ANT-0908ST-295	Frequency Range: 289MHz – 301MHz
PN: 08-ANT-0908ST-254	Frequency Range: 248MHz – 260MHz	PN: 08-ANT-0908ST-296	Frequency Range: 290MHz – 302MHz
PN: 08-ANT-0908ST-255	Frequency Range: 249MHz – 261MHz	PN: 08-ANT-0908ST-297	Frequency Range: 291MHz – 303MHz
PN: 08-ANT-0908ST-256	Frequency Range: 250MHz – 262MHz	PN: 08-ANT-0908ST-298	Frequency Range: 292MHz – 304MHz
PN: 08-ANT-0908ST-257	Frequency Range: 251MHz – 263MHz	PN: 08-ANT-0908ST-299	Frequency Range: 293MHz – 305MHz
PN: 08-ANT-0908ST-258	Frequency Range: 252MHz – 264MHz	PN: 08-ANT-0908ST-300	Frequency Range: 294MHz – 306MHz
PN: 08-ANT-0908ST-259	Frequency Range: 253MHz – 265MHz	PN: 08-ANT-0908ST-301	Frequency Range: 295MHz – 307MHz
PN: 08-ANT-0908ST-260	Frequency Range: 254MHz – 266MHz	PN: 08-ANT-0908ST-302	Frequency Range: 296MHz – 308MHz
PN: 08-ANT-0908ST-261	Frequency Range: 255MHz – 267MHz	PN: 08-ANT-0908ST-303	Frequency Range: 297MHz – 309MHz
PN: 08-ANT-0908ST-262	Frequency Range: 256MHz – 268MHz	PN: 08-ANT-0908ST-304	Frequency Range: 298MHz – 310MHz
PN: 08-ANT-0908ST-263	Frequency Range: 257MHz – 269MHz	PN: 08-ANT-0908ST-305	Frequency Range: 299MHz – 311MHz
PN: 08-ANT-0908ST-264	Frequency Range: 258MHz – 270MHz	PN: 08-ANT-0908ST-306	Frequency Range: 300MHz – 312MHz
PN: 08-ANT-0908ST-265	Frequency Range: 259MHz – 271MHz	PN: 08-ANT-0908ST-307	Frequency Range: 301MHz – 313MHz
PN: 08-ANT-0908ST-266	Frequency Range: 260MHz – 272MHz	PN: 08-ANT-0908ST-308	Frequency Range: 302MHz – 314MHz
PN: 08-ANT-0908ST-267	Frequency Range: 261MHz – 273MHz	PN: 08-ANT-0908ST-309	Frequency Range: 303MHz – 315MHz
PN: 08-ANT-0908ST-268	Frequency Range: 262MHz – 274MHz	PN: 08-ANT-0908ST-310	Frequency Range: 304MHz – 316MHz
PN: 08-ANT-0908ST-269	Frequency Range: 263MHz – 275MHz	PN: 08-ANT-0908ST-311	Frequency Range: 305MHz – 317MHz
PN: 08-ANT-0908ST-270	Frequency Range: 264MHz – 276MHz	PN: 08-ANT-0908ST-312	Frequency Range: 306MHz – 318MHz
PN: 08-ANT-0908ST-271	Frequency Range: 265MHz – 277MHz	PN: 08-ANT-0908ST-313	Frequency Range: 307MHz – 319MHz
PN: 08-ANT-0908ST-272	Frequency Range: 266MHz – 278MHz	PN: 08-ANT-0908ST-314	Frequency Range: 308MHz – 320MHz
PN: 08-ANT-0908ST-273	Frequency Range: 267MHz – 279MHz	PN: 08-ANT-0908ST-315	Frequency Range: 309MHz – 321MHz
PN: 08-ANT-0908ST-274	Frequency Range: 268MHz – 280MHz	PN: 08-ANT-0908ST-316	Frequency Range: 310MHz – 322MHz
PN: 08-ANT-0908ST-275	Frequency Range: 269MHz – 281MHz	PN: 08-ANT-0908ST-317	Frequency Range: 311MHz – 323MHz



# OMNI DAS Antenna

## MULTI-POLARIZED DAS ANTENNA

PN: 08-ANT-0908ST-318	Frequency Range: 312MHz – 324MHz	PN: 08-ANT-0908ST-360	Frequency Range: 354MHz – 366MHz
PN: 08-ANT-0908ST-319	Frequency Range: 313MHz – 325MHz	PN: 08-ANT-0908ST-361	Frequency Range: 355MHz – 367MHz
PN: 08-ANT-0908ST-320	Frequency Range: 314MHz – 326MHz	PN: 08-ANT-0908ST-362	Frequency Range: 356MHz – 368MHz
PN: 08-ANT-0908ST-321	Frequency Range: 315MHz – 327MHz	PN: 08-ANT-0908ST-363	Frequency Range: 357MHz – 369MHz
PN: 08-ANT-0908ST-322	Frequency Range: 316MHz – 328MHz	PN: 08-ANT-0908ST-364	Frequency Range: 358MHz – 370MHz
PN: 08-ANT-0908ST-323	Frequency Range: 317MHz – 329MHz	PN: 08-ANT-0908ST-365	Frequency Range: 359MHz – 371MHz
PN: 08-ANT-0908ST-324	Frequency Range: 318MHz – 330MHz	PN: 08-ANT-0908ST-366	Frequency Range: 360MHz – 372MHz
PN: 08-ANT-0908ST-325	Frequency Range: 319MHz – 331MHz	PN: 08-ANT-0908ST-367	Frequency Range: 361MHz – 373MHz
PN: 08-ANT-0908ST-326	Frequency Range: 320MHz – 332MHz	PN: 08-ANT-0908ST-368	Frequency Range: 362MHz – 374MHz
PN: 08-ANT-0908ST-327	Frequency Range: 321MHz – 333MHz	PN: 08-ANT-0908ST-369	Frequency Range: 363MHz – 375MHz
PN: 08-ANT-0908ST-328	Frequency Range: 322MHz – 334MHz	PN: 08-ANT-0908ST-370	Frequency Range: 364MHz – 376MHz
PN: 08-ANT-0908ST-329	Frequency Range: 323MHz – 335MHz	PN: 08-ANT-0908ST-371	Frequency Range: 365MHz – 377MHz
PN: 08-ANT-0908ST-330	Frequency Range: 324MHz – 336MHz	PN: 08-ANT-0908ST-372	Frequency Range: 366MHz – 378MHz
PN: 08-ANT-0908ST-331	Frequency Range: 325MHz – 337MHz	PN: 08-ANT-0908ST-373	Frequency Range: 367MHz – 379MHz
PN: 08-ANT-0908ST-332	Frequency Range: 326MHz – 338MHz	PN: 08-ANT-0908ST-374	Frequency Range: 368MHz – 380MHz
PN: 08-ANT-0908ST-333	Frequency Range: 327MHz – 339MHz	PN: 08-ANT-0908ST-375	Frequency Range: 369MHz – 381MHz
PN: 08-ANT-0908ST-334	Frequency Range: 328MHz – 340MHz	PN: 08-ANT-0908ST-376	Frequency Range: 370MHz – 382MHz
PN: 08-ANT-0908ST-335	Frequency Range: 329MHz – 341MHz	PN: 08-ANT-0908ST-377	Frequency Range: 371MHz – 383MHz
PN: 08-ANT-0908ST-336	Frequency Range: 330MHz – 342MHz	PN: 08-ANT-0908ST-378	Frequency Range: 372MHz – 384MHz
PN: 08-ANT-0908ST-337	Frequency Range: 331MHz – 343MHz	PN: 08-ANT-0908ST-379	Frequency Range: 373MHz – 385MHz
PN: 08-ANT-0908ST-338	Frequency Range: 332MHz – 344MHz	PN: 08-ANT-0908ST-380	Frequency Range: 374MHz – 386MHz
PN: 08-ANT-0908ST-339	Frequency Range: 333MHz – 345MHz	PN: 08-ANT-0908ST-381	Frequency Range: 375MHz – 387MHz
PN: 08-ANT-0908ST-340	Frequency Range: 334MHz – 346MHz	PN: 08-ANT-0908ST-382	Frequency Range: 376MHz – 388MHz
PN: 08-ANT-0908ST-341	Frequency Range: 335MHz – 347MHz	PN: 08-ANT-0908ST-383	Frequency Range: 377MHz – 389MHz
PN: 08-ANT-0908ST-342	Frequency Range: 336MHz – 348MHz	PN: 08-ANT-0908ST-384	Frequency Range: 378MHz – 390MHz
PN: 08-ANT-0908ST-343	Frequency Range: 337MHz – 349MHz	PN: 08-ANT-0908ST-385	Frequency Range: 379MHz – 391MHz
PN: 08-ANT-0908ST-344	Frequency Range: 338MHz – 350MHz	PN: 08-ANT-0908ST-386	Frequency Range: 380MHz – 392MHz
PN: 08-ANT-0908ST-345	Frequency Range: 339MHz – 351MHz	PN: 08-ANT-0908ST-387	Frequency Range: 381MHz – 393MHz
PN: 08-ANT-0908ST-346	Frequency Range: 340MHz – 352MHz	PN: 08-ANT-0908ST-388	Frequency Range: 382MHz – 394MHz
PN: 08-ANT-0908ST-347	Frequency Range: 341MHz – 353MHz	PN: 08-ANT-0908ST-389	Frequency Range: 383MHz – 395MHz
PN: 08-ANT-0908ST-348	Frequency Range: 342MHz – 354MHz	PN: 08-ANT-0908ST-390	Frequency Range: 384MHz – 396MHz
PN: 08-ANT-0908ST-349	Frequency Range: 343MHz – 355MHz	PN: 08-ANT-0908ST-391	Frequency Range: 385MHz – 397MHz
PN: 08-ANT-0908ST-350	Frequency Range: 344MHz – 356MHz	PN: 08-ANT-0908ST-392	Frequency Range: 386MHz – 398MHz
PN: 08-ANT-0908ST-351	Frequency Range: 345MHz – 357MHz	PN: 08-ANT-0908ST-393	Frequency Range: 387MHz – 399MHz
PN: 08-ANT-0908ST-352	Frequency Range: 346MHz – 358MHz	PN: 08-ANT-0908ST-394	Frequency Range: 388MHz – 400MHz
PN: 08-ANT-0908ST-353	Frequency Range: 347MHz – 359MHz	PN: 08-ANT-0908ST-395	Frequency Range: 389MHz – 401MHz
PN: 08-ANT-0908ST-354	Frequency Range: 348MHz – 360MHz	PN: 08-ANT-0908ST-396	Frequency Range: 390MHz – 402MHz
PN: 08-ANT-0908ST-355	Frequency Range: 349MHz – 361MHz	PN: 08-ANT-0908ST-397	Frequency Range: 391MHz – 403MHz
PN: 08-ANT-0908ST-356	Frequency Range: 350MHz – 362MHz	PN: 08-ANT-0908ST-398	Frequency Range: 392MHz – 404MHz
PN: 08-ANT-0908ST-357	Frequency Range: 351MHz – 363MHz	PN: 08-ANT-0908ST-399	Frequency Range: 393MHz – 405MHz
PN: 08-ANT-0908ST-358	Frequency Range: 352MHz – 364MHz	PN: 08-ANT-0908ST-400	Frequency Range: 394MHz – 406MHz
PN: 08-ANT-0908ST-359	Frequency Range: 353MHz – 365MHz	PN: 08-ANT-0908ST-401	Frequency Range: 395MHz – 407MHz



# OMNI DAS Antenna

## MULTI-POLARIZED DAS ANTENNA

PN: 08-ANT-0908ST-402	Frequency Range: 396MHz – 408MHz	PN: 08-ANT-0908ST-444	Frequency Range: 438MHz – 450MHz
PN: 08-ANT-0908ST-403	Frequency Range: 397MHz – 409MHz	PN: 08-ANT-0908ST-445	Frequency Range: 439MHz – 451MHz
PN: 08-ANT-0908ST-404	Frequency Range: 398MHz – 410MHz	PN: 08-ANT-0908ST-446	Frequency Range: 440MHz – 452MHz
PN: 08-ANT-0908ST-405	Frequency Range: 399MHz – 411MHz	PN: 08-ANT-0908ST-447	Frequency Range: 441MHz – 453MHz
PN: 08-ANT-0908ST-406	Frequency Range: 400MHz – 412MHz	PN: 08-ANT-0908ST-448	Frequency Range: 442MHz – 454MHz
PN: 08-ANT-0908ST-407	Frequency Range: 401MHz – 413MHz	PN: 08-ANT-0908ST-449	Frequency Range: 443MHz – 455MHz
PN: 08-ANT-0908ST-408	Frequency Range: 402MHz – 414MHz	PN: 08-ANT-0908ST-450	Frequency Range: 444MHz – 456MHz
PN: 08-ANT-0908ST-409	Frequency Range: 403MHz – 415MHz	PN: 08-ANT-0908ST-451	Frequency Range: 445MHz – 457MHz
PN: 08-ANT-0908ST-410	Frequency Range: 404MHz – 416MHz	PN: 08-ANT-0908ST-452	Frequency Range: 446MHz – 458MHz
PN: 08-ANT-0908ST-411	Frequency Range: 405MHz – 417MHz	PN: 08-ANT-0908ST-453	Frequency Range: 447MHz – 459MHz
PN: 08-ANT-0908ST-412	Frequency Range: 406MHz – 418MHz	PN: 08-ANT-0908ST-454	Frequency Range: 448MHz – 460MHz
PN: 08-ANT-0908ST-413	Frequency Range: 407MHz – 419MHz	PN: 08-ANT-0908ST-455	Frequency Range: 449MHz – 461MHz
PN: 08-ANT-0908ST-414	Frequency Range: 408MHz – 420MHz	PN: 08-ANT-0908ST-456	Frequency Range: 450MHz – 462MHz
PN: 08-ANT-0908ST-415	Frequency Range: 409MHz – 421MHz	PN: 08-ANT-0908ST-457	Frequency Range: 451MHz – 463MHz
PN: 08-ANT-0908ST-416	Frequency Range: 410MHz – 422MHz	PN: 08-ANT-0908ST-458	Frequency Range: 452MHz – 464MHz
PN: 08-ANT-0908ST-417	Frequency Range: 411MHz – 423MHz	PN: 08-ANT-0908ST-459	Frequency Range: 453MHz – 465MHz
PN: 08-ANT-0908ST-418	Frequency Range: 412MHz – 424MHz	PN: 08-ANT-0908ST-460	Frequency Range: 454MHz – 466MHz
PN: 08-ANT-0908ST-419	Frequency Range: 413MHz – 425MHz	PN: 08-ANT-0908ST-461	Frequency Range: 455MHz – 467MHz
PN: 08-ANT-0908ST-420	Frequency Range: 414MHz – 426MHz	PN: 08-ANT-0908ST-462	Frequency Range: 456MHz – 468MHz
PN: 08-ANT-0908ST-421	Frequency Range: 415MHz – 427MHz	PN: 08-ANT-0908ST-463	Frequency Range: 457MHz – 469MHz
PN: 08-ANT-0908ST-422	Frequency Range: 416MHz – 428MHz	PN: 08-ANT-0908ST-464	Frequency Range: 458MHz – 470MHz
PN: 08-ANT-0908ST-423	Frequency Range: 417MHz – 429MHz	PN: 08-ANT-0908ST-465	Frequency Range: 459MHz – 471MHz
PN: 08-ANT-0908ST-424	Frequency Range: 418MHz – 430MHz	PN: 08-ANT-0908ST-466	Frequency Range: 460MHz – 472MHz
PN: 08-ANT-0908ST-425	Frequency Range: 419MHz – 431MHz	PN: 08-ANT-0908ST-467	Frequency Range: 461MHz – 473MHz
PN: 08-ANT-0908ST-426	Frequency Range: 420MHz – 432MHz	PN: 08-ANT-0908ST-468	Frequency Range: 462MHz – 474MHz
PN: 08-ANT-0908ST-427	Frequency Range: 421MHz – 433MHz	PN: 08-ANT-0908ST-469	Frequency Range: 463MHz – 475MHz
PN: 08-ANT-0908ST-428	Frequency Range: 422MHz – 434MHz	PN: 08-ANT-0908ST-470	Frequency Range: 464MHz – 476MHz
PN: 08-ANT-0908ST-429	Frequency Range: 423MHz – 435MHz	PN: 08-ANT-0908ST-471	Frequency Range: 465MHz – 477MHz
PN: 08-ANT-0908ST-430	Frequency Range: 424MHz – 436MHz	PN: 08-ANT-0908ST-472	Frequency Range: 466MHz – 478MHz
PN: 08-ANT-0908ST-431	Frequency Range: 425MHz – 437MHz	PN: 08-ANT-0908ST-473	Frequency Range: 467MHz – 479MHz
PN: 08-ANT-0908ST-432	Frequency Range: 426MHz – 438MHz	PN: 08-ANT-0908ST-474	Frequency Range: 468MHz – 480MHz
PN: 08-ANT-0908ST-433	Frequency Range: 427MHz – 439MHz	PN: 08-ANT-0908ST-475	Frequency Range: 469MHz – 481MHz
PN: 08-ANT-0908ST-434	Frequency Range: 428MHz – 440MHz	PN: 08-ANT-0908ST-476	Frequency Range: 470MHz – 482MHz
PN: 08-ANT-0908ST-435	Frequency Range: 429MHz – 441MHz	PN: 08-ANT-0908ST-477	Frequency Range: 471MHz – 483MHz
PN: 08-ANT-0908ST-436	Frequency Range: 430MHz – 442MHz	PN: 08-ANT-0908ST-478	Frequency Range: 472MHz – 484MHz
PN: 08-ANT-0908ST-437	Frequency Range: 431MHz – 443MHz	PN: 08-ANT-0908ST-479	Frequency Range: 473MHz – 485MHz
PN: 08-ANT-0908ST-438	Frequency Range: 432MHz – 444MHz	PN: 08-ANT-0908ST-480	Frequency Range: 474MHz – 486MHz
PN: 08-ANT-0908ST-439	Frequency Range: 433MHz – 445MHz	PN: 08-ANT-0908ST-481	Frequency Range: 475MHz – 487MHz
PN: 08-ANT-0908ST-440	Frequency Range: 434MHz – 446MHz	PN: 08-ANT-0908ST-482	Frequency Range: 476MHz – 488MHz
PN: 08-ANT-0908ST-441	Frequency Range: 435MHz – 447MHz	PN: 08-ANT-0908ST-483	Frequency Range: 477MHz – 489MHz
PN: 08-ANT-0908ST-442	Frequency Range: 436MHz – 448MHz	PN: 08-ANT-0908ST-484	Frequency Range: 478MHz – 490MHz
PN: 08-ANT-0908ST-443	Frequency Range: 437MHz – 449MHz	PN: 08-ANT-0908ST-485	Frequency Range: 479MHz – 491MHz





DATA SHEET

# OMNI DAS Antenna

MULTI-POLARIZED DAS ANTENNA

PN: 08-ANT-0908ST-486	Frequency Range: 480MHz – 492MHz
PN: 08-ANT-0908ST-487	Frequency Range: 481MHz – 493MHz
PN: 08-ANT-0908ST-488	Frequency Range: 482MHz – 494MHz
PN: 08-ANT-0908ST-489	Frequency Range: 483MHz – 495MHz
PN: 08-ANT-0908ST-490	Frequency Range: 484MHz – 496MHz
PN: 08-ANT-0908ST-491	Frequency Range: 485MHz – 497MHz
PN: 08-ANT-0908ST-492	Frequency Range: 486MHz – 498MHz
PN: 08-ANT-0908ST-493	Frequency Range: 487MHz – 499MHz
PN: 08-ANT-0908ST-494	Frequency Range: 488MHz – 500MHz
PN: 08-ANT-0908ST-495	Frequency Range: 489MHz – 501MHz
PN: 08-ANT-0908ST-496	Frequency Range: 490MHz – 502MHz
PN: 08-ANT-0908ST-497	Frequency Range: 491MHz – 503MHz
PN: 08-ANT-0908ST-498	Frequency Range: 492MHz – 504MHz
PN: 08-ANT-0908ST-499	Frequency Range: 493MHz – 505MHz
PN: 08-ANT-0908ST-500	Frequency Range: 494MHz – 506MHz

rethink the antenna™

MP Antenna reserves the right to change product information and specifications without notice. Responsibility for the use and application of MP Antenna products rests with the end user since MP Antenna cannot be aware of all potential uses. MP Antenna makes no warranties as to the fitness, merchantability, or suitability of any MP Antenna products for any specific or general uses. MP Antenna shall not be liable for incidental or consequential damages of any kind.\* MP Antenna products and technology are protected under one or more of the United States Patents 6,496,152 6,806,841 7,030,831 7,138,956 7,236,129 7,348,933 7,791,555 7,916,097 D,623,633 D,634,308 and other United States and Foreign patents applied for.